



The **CWE Series** is a wet location exit sign, featuring a polycarbonate housing and waterproof design suitable for wet location. The CWE series can be wall, ceiling or end mounted.

Project: _____
 Location: _____
 Cat.No: _____
 Type: _____
 Lamps: _____ Qty: _____
 Notes: _____

Ordering guide

| Family | Power | Letter Color | Housing | Faces |
|------------------------------|--|--------------------------------|----------------------------------|------------------------------------|
| CWE Wet Location Exit | A AC only N NiCad battery | R Red G Green | W White B Black | U-1 Single/Double faceplate |

Specifications

Codes and standards

- UL listed to standard 924
- NFPA 101 (Life Safety Code)
- UL listed for wet locations (0° C - 50° C)
- Meets CEC title 20 regulations

Power Consumption

- AC version: 120/277 VAC dual voltage input, 2W, 25mA
- Battery version: 2.2W, 25mA

Construction

- Housing constructed of 5VA flame retardant, UV stabilized polycarbonate
- High impact resistant, UV stabilized polycarbonate clear lens
- Corrosion resistant enclosure with engineering grade silicone gasket

Mounting

- Suitable for wall mount, ceiling mount and side mount
- Universal knock-out pattern on back plate for wall mount

Battery

- Maintenance-free, 3.6V rechargeable NiCd (NiCad) battery
- Provides a minimum of 90 minutes of emergency power and takes 24 hours to recharge
- Must be recharged at least once in 9 months

Electronics

- LED indicator light alerts occupant on battery condition (Green-normal, Red-check battery)
- Internal solid-state transfer switch automatically connects the internal battery to LED board for minimum 90-minute emergency illumination
- Battery-powered models include brownout detection, AC lockout, low voltage disconnect, AC power indicator and push-to-test switch
- Battery-powered models support self-diagnostic feature to ensure reliable operation and compliance with electrical and life-safety codes. Tests are executed monthly for 1 minute and annually for 90 minutes

Warranty

- Five-year limited warranty on all electronics and housing. Two-year warranty on the battery.
- Battery must be recharged at least once in 9 months

